



3695 ELECTRONIC VOLTAGE BURDEN

Programmable Electronic Voltage Burden



PROGRAMMABLE ELECTRONIC VOLTAGE BURDEN

The Tettex Instruments Division of Haefely Test AG has designed a programmable electronic voltage burden for efficient testing of instrument transformers. In conjunction with the type 2767 automatic instrument transformer test set and the type 4860 electronic voltage divider, the system makes it possible to integrate burdens into a computer-controlled testing system.

The electronic voltage burden replaces traditional burdens with passive resistances and inductances. The wide range of programmable impedances makes it possible to emulate most existing national and international standard burdens as well as customer-specific values.

FEATURES AND BENEFITS

- The **universal voltage burden** is suitable for standard voltage ratings. Power levels are selectable over a wide range (up to **75 VA**) with $\cos \beta = 0.1$ to 1 at 50 and 60 Hz.
- The **power range can be extended to 400 VA** with an additional passive voltage burden.
- Cost-effectiveness: many classical passive burdens can be replaced by a single electronic voltage burden.
- Burden values can be retrieved from stored tables based on **IEC 60044-2**, **ANSI C57.13** and VDE 0414 Part 2.
- **Nine separate burden settings** (S_N , $\cos \beta$) can be stored and retrieved as needed
- **High accuracy of 1%** - even with additional passive burden connected.
- The internal resistance of the measuring system can be parameterised from the keyboard and is automatically compensated. The unit can thus be used with a variety of instrument transformer test sets, such as Tettex types 2711/22, 2765 and 2767 or other makes.
- Prompting for interactive input of parameters makes operation simple.
- The unit can be totally integrated into an automatic measurement system via the RS – 232 or optional IEEE 488 GPIB interface.

APPLICATIONS

The programmable electronic voltage burden Tettex 3695 is mostly used by:

- Manufacturer of voltage instrument transformers
- Calibration laboratories
- National Standards Laboratories
- On-Site Testing of high voltage instrument transformers

SPECIFICATIONS

Rated power S_N	0; 1 to 75 VA
In increments of	0.01 VA
Power factor $\cos \beta$	1 to 35 VA: 0.1 to 1 ind. 35 to 75 VA: 0.5 to 1 ind.
In increments of	0.01
Rated voltages U_N	100 / 110 / 115 / 120 / 200 / 230 V
All values with factors of	1/1, 1/√3 and 1/3
Voltage range	2 to 190% U_N
Maximum burden current	12 A
Test voltage frequency	48 to 62 Hz
Error thresholds:	
- under reference conditions:	
Test voltage frequency	50 or 60 Hz
Resistance $\Delta R / Z $	$\pm 1 \% *$
Reactance $\Delta X / Z $	$\pm 1 \% *$
- under rated service conditions:	
Resistance $\Delta R / Z $	$\pm 3 \% *$
Reactance $\Delta X / Z $	$\pm 3 \% *$
- at 0 VA setting	$S < 0.05 \text{ VA}$
Cited error thresholds also apply when additional burden is connected.	
Reference and rated service conditions according to IEC 359 and operating instructions.	
Line power	230 or 115 V, 50 or 60 Hz
Power consumption	Approx. 620 VA
Temperature range	+5 to +40 °C
Dimensions (W x H x D)	500 x 320 x 470 mm
Weight	Approx. 50 kg

*) $|Z| = \text{impedance} = IR + jXI$

SCOPE OF SUPPLY

Programmable electronic voltage burden 3695, power cable
Please specify line voltage when ordering (230 V / 50 Hz or 110 V / 60 Hz).

ACCESSORIES & OPTIONS

3697

Remotely controlled additional passive voltage burden with automatic detection of possible burden range S_N , U_N and $\cos \beta$ by 3695. Expands the range to max. 400 VA.

Rated power S_N	75 to 400 VA
Rated voltages U_N	100 / 110 V
All values with factors of	1/1, 1/√3 and 1/3
Power factor $\cos \beta$	0.8 and 0.85
Test voltage frequency	50 and 60 Hz

3695 / 1

Interface (IEEE 488 GPIB) for remote control by external computer, incl. data cable.
Disables standard RS – 232 interface.

Tettex Instruments offers a complete portfolio for instrument transformer testing



2767

Automatic Instrument Transformer Test Set

Highly accurate test set for accuracy measurements of voltage and current instrument transformers according IEC60044, ANSI C57.13 and others.

3691

Electronic Current Burden

Programmable electronic current burden according IEC, ANSI or user defined values. Up to a rated power of 75 VA with 1% accuracy. Can be extended to 200 VA with external burden Tettex 3692.



4860

Standard Electronic Voltage Divider

Electronic voltage divider used as a variable comparison standard (replacement of inductive nominal voltage transformers). Voltage Ranges from 1 kV to 800 kV or higher.

4761 / 64

Current Comparators

Electronically compensated current comparator with an accuracy of 10 ppm and 0.05 min. User settable ratios of 1 / 5 A to 1000 or 5000 A.



5270

High Voltage Power Supplies

As part of the Haefely Test AG, Tettex can offer a variety of high voltage sources.

5260

High Current Power Supply

Current power supply from 2 kA up to 10 kA (higher on customer request) for instrument transformer testing.



Europe, Asia, South & Central

America, Australia

Haefely Test AG
Birsstrasse 300
4052 Basel
Switzerland
☎ +41 61 373 4111
✉ +41 61 373 4912
sales@tettex.com

China (Sales & Service Office)

Haefely Test AG – Beijing Office
8-1-602, Fortune Street
No. 67, Chaoyang Road, Chaoyang District
Beijing, 100025
P. R. China
☎ +86 10 8578 8099
✉ +86 10 8578 9908
sales@haefely.com.cn

North America

Hipotronics Inc.
1650 Route 22
PO Box 414
Brewster, NY 10509
USA
☎ +1 845 279 3644
✉ +1 845 279 2467
sales@hipotronics.com

a brand of

HAEFELY 


precision.
swiss made.

Haefely is a subsidiary
of Hubbell Incorporated.

 High Voltage
Test Business